

The S-PIR is a self-contained motion detector with built in GSM modem for sending a SMS Text message to you when the zone is breached.

Just register the pay-as-you-go SIM card with some credit and insert into the S-PIR, plug in the mains transformer and you are ready to configure.

Then by SMS change the security pass code and add your mobile number.

To "arm" just "ring" the S-PIR for a few seconds and you have 15 seconds to leave the secure area. Its now armed.

When the PIR sensor next detects motion you will receive a SMS informing you.

The S-PIR will then call you so you can hear (via the units built-in microphone) and activity at the remote location.



Features

- ▶ PIR Motion Detector.
- ▶ Built-in GSM (mobile) modem - just add a SIM card. (UK PAYG supplied with S-PIR).
- ▶ Send SMS to up to 5 numbers - (you, neighbour, estate manager etc)
- ▶ Name the zone - e.g. "Home", "Office", "Garage" etc.
- ▶ Built-in microphone - S-PIR calls you back to allow you to listen in at the location
- ▶ Battery backup - rechargeable battery will inform you of power fail, low battery and power resume.
- ▶ Arm just by ringing from your authorised number.
- ▶ Exit delay (Adjustable).

Specification

Power

Power 11-15vDC, 500mA max - can be powered from an external leisure battery.

Battery Backup 8.4vDC, 150-250mAh, Ni-Mh

Battery Operating Time (Max)
up to 6 hours

PIR

Detection Range 10 meters

Detection Angle 90°

GSM

Dual Band 900/1800MHz



In the box

S-PIR Unit plus

SIM Card Select network at time of order - Vodafone, O2, Orange or T-Mobile (UK PAYG - No credit)

Antenna Internal Antenna

Power Supply Plug in 100-240vAC to 15vDC plug in power supply provided (5m lead)

User Guide Quick start user guide - advanced manual at www.sendtech.co.uk

Dimensions

Dimensions 104hx60wx33dmm

Mounting Options: Wall Mounting bracket supplied

Ordering Information

Part No: **S-PIR** Price **£129.00** ex VAT
Delivery **£8.50** (Next Day UK)

